





Digital Migration Radio

MD612 & SERIES



- ➤ Analog & Digital Dual Modes
- > Remote Control Head
- > Clear Voice
- ➤ GPS and Bluetooth Option





PROFESSIONAL AND SIMPLE TO USE



A&D Auto Detect

Compatible with analog conventional and digital conventional modes. Allow MD612i to simultaneously monitor analog and digital modes and automatically respond in each mode. It is an easy way for migration to digital from analog.



INCREASED COVERAGE RANGE

With a high RF power output up to 50W, MD612i can dramatically increase your communication range



GPS POSITIONING (Optional)

With an external GPS module and GPS antenna, MD612i can upload its real-time position to AVL applications.



REMOTE CONTROL HEAD(Coming soon)

Remote control head kit reduces your concerns of installation, and offers you a flexible solution for various vehicle types.



ANALOG SIGNALING

Support DTMF and HDC1200(coming soon) signaling in analog mode.



RELIABLE AND DURABLE

MD612i is compliant with MIL-STD-810 C/D/E/F/G and IP54.



PSEUDO TRUNK

Several talk groups share the same frequency, and each one of them can dynamically chose to use one of the slots to talk. This is a two-slot-trunked mode. While time-slot 1 is busy, MD612i will use time-slot 2 to transmit.



RADIO REGISTRATION SERVICE

RRS allows MD612i working in Smart Dispatch and SmartOne Dispatch, for online/offline presence.



SUPPLEMENTARY FEATURES (Optional)

MD612i supports radio Enable/Disable, Remoter Monitor and Priority Interrupt.



EMERGENCY ALARM/CALL

Use the orange emergency button to initiate an emergency alarm and call to other radios.



BUILT-IN BLUETOOTH (Factory Optional)

Built-in Bluetooth supports MD612i to support wireless audio accessories and PTT devices to provide hands-free operation.



PRIVACY

Basic end-to-end Encryption secures your voice and data transmission.



ROAMING (Optional)

It allows MD612i to be used in a large multi-site network.

TARGET MARKETS



ACCESSORIES



SPECIFICATIONS

		GENERAL	
Frequency Range		UHF: 400-470MHz; VHF: 136-174MHz	
Channel Capacity		48 (16 channels per zone)	
Zone Capacity		3	
Channel spacing		12.5 / 25 KHz	
Operating Voltage		13.6 V ±15%	
Current Drain	Standby	around 0.3A	
	Receive	< 1 A	
	Transmit	1W	<3A
		25W	<8A
		5W	<5A
		45W	<12A
Weight		1100g	
Dimensions		164 X 43 X 150 mm	
Frequency Stability		±0.5 ppm	
Antenna Impedance		50Ω	
		RECEIVER	
Sensitivity	Analog	0.3µV (12dB SINAD); 0.22µV (Typical) (12dB SINAD); 0.4µV (20dB SINAD)	
	Digital	0.3μV /BER5%	
Selectivity	TIA-603	60dB @ 12.5KHz / 70dB @ 25KHz"	
	ETSI	60dB @ 12.5KHz / 70dB @ 25KHz [#]	
Intermodulation	TIA-603	70dB @ 12.5/25KHz [®]	
	ETSI	65dB @ 12.5/25KHz"	
Spurious Response Rejection	TIA-603	70dB @ 12.5/25KHz"	
	ETSI	70dB @ 12.5/25KHz	
Blocking	TIA-603	90dB	
	ETSI	84dB	
Hum and Noise		40dB @ 12.5KHz 45dB @ 25KHz"	
Rated Audio Power Output		Internal (@16 ohm load)	4W
		External (@8 ohm load)	8W
Max Audio Power Output		Internal (@16 ohm load)	6W
		External (@8 ohm load)	12W
Rated Audio Distortion		≤3%	
Audio Response		+1 ~ -3dB	
Caradorata d Caroniana Fasianian		10	

	TOANICAUTTED			
	TRANSMITTER			
RF Power Output	Low power version: 1-25W (UHF/VHF) High power version: 5-45W(UHF) / 5-50W(VHF)			
FM Modulation	11K0F3E @ 12.5KHz; 16K0F3E @ 25KHz [#]			
4FSK Digital Modulation	12.5KHz Data Only: 7K60FXD 12.5KHz Data & Voice: 7K60FXW			
Conducted/Radiated Emission	-36dBm<1GHz; -30dBm>1GHz			
Modulation Limiting	±2.5KHz @ 12.5KHz ±5.0KHz @ 25KHz [*]			
FM Hum & Noise	40dB @ 12.5KHz 45dB @ 25KHz"			
Adjacent Channel Power	60dB @ 12.5KHz; 70dB @ 25KHz"			
Audio Response	+1 ~ -3dB			
Audio Distortion	≤3%			
Digital Vocoder Type	AMBE+2 TM			
Digital Protocol	ETSI-TS102 361-1,-2,-3			
ENVIRONMENTAL				
Operating Temperature	-30°C~ +60°C			
Storage Temperature	-40°C~ +85°C			
ESD	IEC 61000-4-2 (Level 4) ±8kV (Contact) ±15kV (Air)			
American Military Standard	MIL-STD-810 G			
Dustproof & Waterproof	IP54 Standard			
Humidity	MIL-STD-810 G Standard			
Shock & Vibration	MIL-STD-810 G Standard			

¹²20KHz/25KHz will not be available on new equipment in the U.S. after 2011-01-01. All specifications are subject to change without notice due to continuous development.



Conducted Spurious Emission





<-57dBm





3315 Commerce Parkway, Miramar, FL 33025, United States Telephone: +1(954)846-1011

8 Whatney, Suite 200, Irvine, CA 92618, United States Telephone: +1(949)326-5740

1916 Wright Boulevard, Schaumburg, IL 60193, United States Telephone: +1 (213) 262-3578

Hytera Authorized Dealer: Alpha Prime Communications Sales . Rentals . Service 1808 Janke Drive, Suite E Northbrook, IL 60062 USA $847\hbox{-}298\hbox{-}4000 \ . \ service@alphaprimecomm.com}$

Hytera retains right to change the product design and specification. Should any printing mistake occur, Hytera doesn't bear relevant responsibility. Little difference between real product and product indicated by printing materials will occur by printing reason.